# **Product datasheet**

Specifications





High power contactor, TeSys Giga, 4 pole (4NO), AC-1 <=440V 275A, standard version, 100...250V wide band AC/DC coil

LC1G1504KUEN

### Main

Range	TeSys	
Range Of Produc	TeSys Giga	
Product Or Component Type	Contactor	
Device Short Name	LC1G	
Contactor Application	Power switching	
Utilisation Category	AC-3 AC-3e AC-1 AC-5a AC-5b AC-6a AC-6b DC-1 DC-3 DC-5	
Poles Description	4P	
[Ue] Rated Operational Voltage	<= 1000 V AC 50/60 Hz <= 460 V DC	
[le] Rated Operational Current	150 A (at <60 °C) at <= 440 V AC-3 275 A (at <40 °C) at <= 1000 V AC-1	
[Uc] Control Circuit Voltage	100250 V AC 50/60 Hz 100250 V DC	
Control Circuit Voltage Limits	Operational: 0.8 Uc Min1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max0.45 Uc Min (at <60 °C)	

## Complementary

[Uimp] Rated Impulse Withstand Voltage	8 kV
Overvoltage Category	III
[Ith] Conventional Free Air Thermal Current	275 A (at 40 °C)
Rated Breaking Capacity	1280 A at 440 V
[Icw] Rated Short-Time Withstand Current	1.2 kA - 10 s 0.7 kA - 30 s 0.6 kA - 1 min 0.45 kA - 3 min 0.35 kA - 10 min
Associated Fuse Rating	160 A aM at <= 440 V for motor 160 A aM at <= 690 V for motor 315 A gG at <= 690 V
Average Impedance	0.00018 Ohm
[Ui] Rated Insulation Voltage	1000 V

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Power Dissipation Per Pole	10 W AC-1 - Ith 275 A 5 W AC-3 - Ith 150 A
Compatibility Code	LC1G
Pole Contact Composition	4 NO
Auxiliary Contact Composition	1 NO + 1 NC
Irms Rated Making Capacity	1890 A at 440 V
Coil Technology	Built-in bidirectional peak limiting
Mechanical Durability	8 Mcycles
Inrush Power In Va (50/60 Hz, Ac)	540 VA
Inrush Power In W (Dc)	380 W
Hold-In Power Consumption In Va (50/60 Hz, Ac)	12.4 VA
Hold-In Power Consumption In W (Dc)	7.8 W
Operating Time	4070 ms closing 1550 ms opening
Maximum Operating Rate	600 cyc/h AC-3 600 cyc/h AC-3e 300 cyc/h AC-1
Connections - Terminals	Power circuit: bar 2 - busbar cross section: 25 x 6 mm  Power circuit: lugs-ring terminals 1 185 mm²  Control circuit: push-in 1 0.22.5 mm² - cable stiffness: solid stranded without cable end  Control circuit: push-in 1 0.252.5 mm² - cable stiffness: flexible with cable end  Control circuit: push-in 2 0.51.0 mm² with cable end  Control circuit: push-in 0.752.5 mm² - cable stiffness: solid stranded without cable end  Control circuit: push-in 0.752.5 mm² - cable stiffness: flexible with cable end
Connection Pitch	35 mm
Connection Pitch  Mounting Support	35 mm Plate
Mounting Support	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1
Mounting Support Standards	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA
Mounting Support Standards  Product Certifications	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
Mounting Support Standards  Product Certifications  Tightening Torque	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
Mounting Support  Standards  Product Certifications  Tightening Torque  Height	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
Mounting Support  Standards  Product Certifications  Tightening Torque  Height  Width  Depth  Net Weight	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  193 mm
Mounting Support  Standards  Product Certifications  Tightening Torque  Height  Width  Depth	Plate  EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  193 mm  143 mm
Mounting Support Standards  Product Certifications  Tightening Torque Height Width Depth Net Weight  Environment	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1  CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL  18 N.m  193 mm  143 mm  193 mm  144 kg

Mechanical Robustness	Vibrations 5300 Hz 2 gn contactor open Vibrations 5300 Hz 4 gn contactor closed Shocks 10 gn 11 ms contactor open Shocks 15 gn 11 ms contactor closed
Colour	Dark grey
Protective Treatment	TH
Permissible Ambient Air Temperature Around The Device	-4070 °C at Uc

# **Packing Units**

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	24.5 cm
Package 1 Width	27.0 cm
Package 1 Length	38.5 cm
Package 1 Weight	5.687 kg
Unit Type Of Package 2	S06
Number Of Units In Package 2	6
Package 2 Height	75 cm
Package 2 Width	60 cm
Package 2 Length	80 cm
Package 2 Weight	44.13 kg



**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >





Transparency RoHS/REACh

### Well-being performance

<b>⊘</b>	Mercury Free
<b>Ø</b>	Rohs Exemption Information Yes
<b>⊘</b>	Pvc Free
<b>⊘</b>	Halogen Free Plastic Parts Product

## **Certifications & Standards**

Reach Regulation	REACh Declaration
Eu Rohs Directive	Compliant with Exemptions
China Rohs Regulation	China RoHS declaration
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information

# **Product datasheet**

#### LC1G1504KUEN

#### Installation

#### **Installation Videos**

TeSys Giga - How to install the auxiliary contact block

TeSys Giga - How to install and remove remote wear diagnosis module

TeSys Giga - How to install mechanical interlock kit

TeSys Giga - How to install cable memory kit

TeSys Giga - How to replace control module

TeSys Giga - How to replace switching modules

TeSys Giga - How to assemble change-over solution