## **Product data sheet**

Specifications



# auxiliary switch AX, EasyPact EZC 100, EasyPact CVS 100BS, 1 common point changeover contact

EZAUX10

VIE	un
-----	----

Range of product	EZC100
Range	EasyPact
Device short name	AX
Product or component type	Switch
Device application	Signalling
Range compatibility	EasyPact (EZC) circuit breaker
Signal contacts composition	1 NO/NC

#### Complementary

Auxiliary contacts type	Standard
[Ith] conventional free air thermal current	5 A
[le] rated operational current	AC-12: 3 A at 250 V AC 50/60 Hz
	AC-12: 5 A at 125 V AC 50/60 Hz
	AC-12: 5 A at 24 V AC 50/60 Hz
	AC-12: 5 A at 48 V AC 50/60 Hz
	AC-15: 2 A at 250 V AC 50/60 Hz
	AC-15: 3 A at 125 V AC 50/60 Hz
	AC-15: 5 A at 24 V AC 50/60 Hz
	AC-15: 5 A at 48 V AC 50/60 Hz
	DC-12: 0.2 A at 250 V DC
	DC-12: 0.4 A at 125 V DC
	DC-12: 2.5 A at 48 V DC
	DC-12: 4 A at 24 V DC
	DC-14: 0.2 A at 250 V DC
	DC-14: 0.4 A at 125 V DC
	DC-14: 1 A at 48 V DC
	DC-14: 3 A at 24 V DC
Minimum load	10 mA at 24 V
Auxiliary connection terminal	Lead wire

#### **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.5 cm
Package 1 Width	7.0 cm
Package 1 Length	8.5 cm
Package 1 Weight	40.0 g

### Offer Sustainability

REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Compliant EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
China RoHS Regulation	China RoHS declaration
RoHS exemption information	Yes
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

#### **Contractual warranty**

Warranty 18 months

Recommended replacement(s)