



# Protection module, Harmony, diode +green LED, for all sockets, 24...60V DC

RZM031BN

M	a	ı	r	

Range of product	Harmony Electromechanical Relays
Accessory / separate part category	Protection accessories
Product or component type	Protection module
Accessory / separate part designation	Diode + green LED
Product compatibility	Socket RSZ (1 C/O) Socket RSZ (2 C/O) Socket RGZ (1 C/O) Socket RGZ (2 C/O)
Product destination	RSB relay
[Uc] control circuit voltage	2460 V DC
Sale per indivisible quantity	10

#### Complementary

Net weight 0.004 kg

### **Packing Units**

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.000 cm
Package 1 Width	1.500 cm
Package 1 Length	3.500 cm
Package 1 Weight	2.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	3.000 cm
Package 2 Width	7.000 cm
Package 2 Length	11.000 cm
Package 2 Weight	19.000 g
Unit Type of Package 3	S03
Number of Units in Package 3	2000

Offer Sustainability		
Package 3 Weight	4.293 kg	
Package 3 Length	40.000 cm	
Package 3 Width	30.000 cm	
Package 3 Height	30.000 cm	

Sustainable offer status	Green Premium product
REACh Regulation	REACh Declaration
REACh free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes
China RoHS Regulation	China RoHS declaration
RoHS exemption information	Yes
Environmental Disclosure	Product Environmental Profile
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

## **Contractual warranty**


Warranty 18 months

# **Product data sheet**

# RZM031BN

Connections and Schema

#### Wiring Diagram



Recommended replacement(s)